



10260 Bandley Drive
Cupertino, California 95014, U.S.A.
Tel. (408) 996-1010 Telex: 339543

Georges -

May 8, 1978

Disk II Operating Instructions (Prototype only)

1. Unpack and open disk drive case (4 round head screws). Check that 3 connectors to PCB did not come loose during shipment.
2. With power off, insert Disk II Interface Card into Apple slot #7 (op system works only in this slot).
3. Power up Apple, CTRL-B into Basic.
4. Insert Floppy disc Demo into Disk II, Apple Logo up.
5. Type PR#7 and depress return button. This will boot up disk operating system.
6. New commands are:
 - A. >DIR (c.r.) Gets directory of demo programs on disk
 - B. >LOAD program name Loads and runs program from disk.
 - C. >LOAD (c.r.) Standard BASIC Cassette tape LOAD.
 - D. >PR#0 (c.r.) Turns off disk.
7. Production DOS will have LOAD & SAVE named programs, and open & close data files.
8. Current plans (may change) is for formatted single density capacity of 110 Kilobytes.

Regards,

Andre Sousan